







T8 LED MCOB



| Kanlux             |       | [W] | Tc [K]    | [lm] | kWh/1000h | [g] |
|--------------------|-------|-----|-----------|------|-----------|-----|
| T8 LED MCOB 8W-WW  | 18800 | 8   | 2700-3200 | 800  | 8         | 200 |
| T8 LED MCOB 8W-NW  | 18801 | 8   | 4000-4500 | 900  | 8         | 200 |
| T8 LED MCOB 12W-WW | 18802 | 12  | 2700-3200 | 1200 | 12        | 380 |
| T8 LED MCOB 12W-NW | 18803 | 12  | 4000-4500 | 1350 | 12        | 380 |
| T8 LED MCOB 16W-WW | 18804 | 16  | 2700-3200 | 1600 | 16        | 380 |
| T8 LED MCOB 16W-NW | 18805 | 16  | 4000-4500 | 1850 | 16        | 380 |
| T8 LED MCOB 18W-WW | 18806 | 18  | 2700-3200 | 1800 | 18        | 380 |
| T8 LED MCOB 18W-NW | 18807 | 18  | 4000-4500 | 2000 | 18        | 380 |
| T8 LED MCOB 23W-WW | 18808 | 23  | 2700-3200 | 2200 | 23        | 470 |
| T8 LED MCOB 23W-NW | 18809 | 23  | 4000-4500 | 2500 | 23        | 470 |



MCOB - Multi Chip on Board / does not work with supplying system / two sided power supply / specialist product - for professional use  
 MCOB - Multi Chip on Board / funktioniert nicht mit Versorgungssystem / zweiseitige Speisung / Spezialprodukt - für professionelle Anwendung bestimmt